PHILIPS

Lighting



MASTER Softone

Master Softone 12W WW E27 220-240V 1PF/6

Energy Saving lamps with design and superior performance, designed for incandescent lamp replacement in professional applications (Hotels, restaurants, etc), where you want to create an intimate and cozy atmosphere. With a comprehensive range of wattages, it enables easy replacement of most incandescent lamp all the way

Product data

General Information	
Cap-Base	E27 [E27]
Nominal Lifetime (Nom)	12000 h
Switching Cycle	30000X

Light Technical	
Color Code	827 [CCT of 2700K]
Luminous Flux (Nom)	630 lm
Luminous Flux (Rated) (Nom)	630 lm
Color Designation	Warm White (WW)
Lumen Maintenance 2000 h (Nom)	83 %
Chromaticity Coordinate X (Nom)	463
Chromaticity Coordinate Y (Nom)	420
Correlated Color Temperature (Nom)	2700 K
Luminous Efficacy (Rated) (Nom)	52.5 lm/W
Color Rendering Index (Min)	81
Color Rendering Index (Nom)	82
LLMF At End Of Nominal Lifetime (Nom)	65 %

Operating and Electrical	
Input Frequency	50 or 60 Hz
Power (Rated) (Nom)	12.0 W
Lamp Current (Nom)	91 mA
Wattage Equivalent	53 W
Starting Time (Nom)	1 s
Warm Up Time to 60% Light (Min)	10 s
Warm Up Time to 60% Light (Max)	100 s
Power Factor (Nom)	0.6
Voltage (Nom)	220-240 V

Controls and Dimming	
Dimmable	No

Approval and Application	
Energy Efficiency Label (EEL)	A
Mercury (Hg) Content (Max)	2.0 mg
Mercury (Hg) Content (Nom)	1.5 mg
Energy Consumption kWh/1000 h	12 kWh

Product Data	
Full product code	871150046806200
Order product name	Master Softone 12W WW E27 220-240V 1PF/6
EAN/UPC - Product	8711500468062
Order code	929689111301
Numerator - Quantity Per Pack	1
Numerator - Packs per outer box	6


MASTER Softone

Material Nr. (12NC)	929689111301
Net Weight (Piece)	0.084 kg

Warnings and Safety

- Breaking a lamp is extremely unlikely to have any impact on your health. If a lamp breaks, ventilate the room for 30 minutes and remove the parts, preferably with gloves. Put them in a closed plastic bag and take it to your local waste facilities for recycling. Do not use a vacuum cleaner.
- Compact fluorescent lamps have to be treated as special waste, they must be taken to your local waste facilities for recycling. The European Lighting Industry has set up an infrastructure, capable of recycling mercury, other metals, glass etc.

Dimensional drawing



Ambiance Erp 12W WW E27 220-240V 50/60Hz

Product	D (max)	C (max)	F (max)
Master Softone 12W WW E27 220-240V 1PF/6	65.8 mm	128.1 mm	48.1 mm

© 2017 Philips Lighting Holding B.V. All rights reserved. Philips Lighting reserves the right to make changes in specifications and/or to discontinue any product at any timewithout notice or obligation and will not be liable for any consequences resulting from the use of this publication.