


# Softone

## Softone 8W WW E27 220-240V 1PF/6

Energy Saving Lamp with Comfort & Design, tailor-made for customers who look for gentle soft light and elegent design, that complement the luminaires beautifully

### Product data

| General Information | |
|---|---|
| Cap-Base | E27 [ E27] |
| Nominal Lifetime (Nom) | 10000 h |
| Switching Cycle | 30000X |

| Light Technical | |
|---|---|
| Color Code | 827 [ CCT of 2700K] |
| Luminous Flux (Nom) | 400 lm |
| Luminous Flux (Rated) (Nom) | 400 lm |
| Color Designation | Warm White (WW) |
| Lumen Maintenance 2000 h (Nom) | 83 % |
| Chromaticity Coordinate X (Nom) | 463 |
| Chromaticity Coordinate Y (Nom) | 420 |
| Correlated Color Temperature (Nom) | 2700 K |
| Luminous Efficacy (Rated) (Nom) | 50 lm/W |
| Color Rendering Index (Min) | 81 |
| Color Rendering Index (Nom) | 82 |
| LLMF At End Of Nominal Lifetime (Nom) | 65 % |

| Operating and Electrical | |
|---|---|
| Input Frequency | 50 or 60 Hz |
| Power (Rated) (Nom) | 8.0 W |
| Lamp Current (Nom) | 60 mA |
| Wattage Equivalent | 38 W |
| Starting Time (Nom) | 1.5 s |
| Warm Up Time to 60% Light (Min) | 10 s |
| Warm Up Time to 60% Light (Max) | 100 s |
| Power Factor (Nom) | 0.6 |
| Voltage (Nom) | 220-240 V |

| Controls and Dimming | |
|---|---|
| Dimmable | No |

| Approval and Application | |
|---|---|
| Energy Efficiency Label (EEL) | A |
| Mercury (Hg) Content (Max) | 2.0 mg |
| Mercury (Hg) Content (Nom) | 1.5 mg |
| Energy Consumption kWh/1000 h | 8 kWh |


| Product Data | |
|---|---|
| Full product code | 871829168187800 |
| Order product name | Softone 8W WW E27 220-240V 1PF/6 |
| EAN/UPC - Product | 8718291681878 |
| Order code | 929689118302 |
| Numerator - Quantity Per Pack | 1 |
| Numerator - Packs per outer box | 6 |
| Material Nr. (12NC) | 929689118302 |
| Net Weight (Piece) | 0.063 kg |

# Softone

## Warnings and Safety

- Breaking a lamp is extremely unlikely to have any impact on your health. If a lamp breaks, ventilate the room for 30 minutes and remove the parts, preferably with gloves. Put them in a closed plastic bag and take it to your local waste facilities for recycling. Do not use a vacuum cleaner.
- Compact fluorescent lamps have to be treated as special waste, they must be taken to your local waste facilities for recycling. The European Lighting Industry has set up an infrastructure, capable of recycling mercury, other metals, glass etc.

## Dimensional drawing




**Ambiance 8W WW E27 220-240V 50/60Hz**

| Product | D (max) | C (max) | F (max) |
|---|---|---|---|
| Softone 8W WW E27 220-240V 1PF/6 | 56.0 mm | 109.0 mm | 45.5 mm |

© 2017 Philips Lighting Holding B.V. All rights reserved. Philips Lighting reserves the right to make changes in specifications and/or to discontinue any product at any timewithout notice or obligation and will not be liable for any consequences resulting from the use of this publication.